

300W - 4000W 12V | 24V to 230V Car Inverter with Pure Sine Wave

- Charge any device (laptops, household electronics, TVs, etc.) on the go.
- Stable & safe conversion.
- Pure sine wave output.
- Built with high quality materials. Protective metallic case.
- Easy to store & transport.
- Digital display shows output voltage (models: 500W, 1000W, 1500W, 2500W, 4000W)
- LED indicators for working / errors.
- Cables included
- Additional output: 1x USB output

Technical Specifications

Power	300 W	500 W	1500 W	2500 W	4000 W	1000 W
Peak Power	600 W	1000 W	3000 W	5000 W	8000 W	2000 W
Input Voltage	12 V					24 V
Input Voltage Range	9.8V-16V (±0.5v)					19.6V-32V (±1V)
Output Voltage	230V AC (±10V)					
Output Frequency	50 Hz					
Outputs	1 x Schuko		2 x Schuko + 1 x USB			
Waveform	Pure Sine Wave					
Protection	Under/over voltage, overload, overtemperature, short circuit					
Dimension LxWxH (mm)	195x110x80	265x150x80	390x165x90	425x165x90	475x150x200	345x165x90
Net Weight	0.85 kg	1.85 kg	3.65 kg	4.3 kg	8.5 kg	2.75 kg
Compatible Batteries	Any 12V batteries					Any 24V bat.

Models:



300W



500W



1000W | 1500W | 2500W



4000W